

WilsonPro A500

Signal Booster Kit for Homes



A500

The WilsonPro A500 (50 Ohm) from Wilson Electronics is the most popular home and small office cell phone signal booster we currently offer. It features a graphical uplink & downlink meter and self-optimizing design for easy install & maintenance.

- Boosts 3G & 4G for any home or building up to 500m²
- Our most popular home and small office booster
- Works for any phone using Major Network providers in Africa
- Complete kit: all parts included, easy install
- Better voice, text & internet guaranteed



ELECTRICAL SPECS

Item No.	A500			
Frequency Bands	MHz	880-915 / 925-960	1710-1785 / 1805-1880	1920-1980 / 2110-2170
Gain UL/DL	dB	80/ 58	71 / 48	74/ 51
Impedance	ohm	50		
Input Power	V and A	5 V / 3 A		

MECHANICAL SPECS

Connector Type		N-Female
Dimensions	cm	4,4 x 11,4 x 16,5
Weight	kg	0.85
Booster Colour		Blue

With up to +70 dB gain of power, it greatly enhances 4G LTE and 3G cell service for all your wireless cellular devices (smartphones, tablets, notebooks, hotspots, etc.) on any network provider in Africa. There are no monthly fees nor does it need to be connected to any internet source (wifi or landline) to work. It simply amplifies your existing in-building cellular service up to 32X for better voice, text, and faster internet. Backed by a 1-year manufacturer warranty, technical support team in Africa, 30-day better signal or money back guarantee, and lifetime technical support.

Goodbye, no-signal frustrations.



QUESTIONS? CALL US TODAY
+27 (010) 157 0190

✉ sales@boltontechnicalafrica.com
🌐 www.boltontechnicalafrica.com

