## The Quicksilver

## Yagi Directional Cellular Antenna



BT974884

Not all Yagi Antennas are created equal. The Quicksilver - a Yagi designed for the modern era. Compact, efficient, and high gain.

- Wide band, 698-2700 MHz, N-Female
- Built for 50 Ohm Signal Boosters
- High efficiency and compact design
- Stable performance proving high gain up to +9 dBi



	JFF		Product Specifications may cl	hange without prior notice.
Item No.		BT974884		
requency Rang	е	MHz	698-960	1710-2700
ain		dBi	8	9
olarization			Vertical & F	Horizontal
	Horizontal		60	55
eam width	Vertical	deg	65	45
SWR			≤1.8	1.5
Maximum Input Power		watt	50	
Impedance		ohm	50	
PIM, 3rd Order, 2 x 2W		dBc	≤-140	
ECHANICAL S	TUFF			
onnector Type			N-Fer	nale
onnector Type onnector Positi	on		N-Fer Botto	
	on	mm, in		om
onnector Positi		mm, in kg, lb	Botto	om .32 x 8.25 x 2.36
onnector Positi ze			Botto 440 x 210 x 60, 17	om 3.32 x 8.25 x 2.36 2.65
onnector Positi ze ntenna Weight ated Wind Velo	ocity	kg, lb	Botto 440 x 210 x 60, 17 1.20, 2	om 2.32 x 8.25 x 2.36 2.65 9, 121
onnector Positi ze ntenna Weight	ocity operature	kg, lb m/s, F/s	Botto 440 x 210 x 60, 17 1.20, 2 36.90	om .32 x 8.25 x 2.36 2.65 , 121 -40 to 131
onnector Positi ze ntenna Weight ated Wind Velc perational Tem	ocity operature vare	kg, lb m/s, F/s °C, °F	Botto 440 x 210 x 60, 17 1.20, 2 36.90 -40 to 55, -	om .32 x 8.25 x 2.36 2.65 9, 121 -40 to 131 .40 to 2.00







